

## C-Band Synthesized Frequency Converter WAAS/EGNOS Compliant



*Low Phase Noise/High Stability  
Synthesized Frequency Converter FCS2001*

### Features

- 51 MHz Input within 1150-1600 MHz
- 51 MHz Output within 6.6-7.075 GHz
- 10 Hz step size
- Fully compliant with WAAS and EGNOS requirements
- High stability
- Low Phase Noise
- Front panel control (local)
- Full remote control (remote)

### Overview

The Advantech Wireless WEK range of converters uses the latest technology in conversion, local and remote control thus providing the ultimate in performance and user friendly operation at a very competitive price.

The spectral purity, low phase noise and stability meet the requirements of all WAAS or EGNOS international satellite network operators.

The flexible and comprehensive monitor and control features on the WE series converters ensure that it will fit into any network management system architecture. The user-friendly front panel or the RS485 remote interface will provide full set-up and fault monitoring facilities. The RS232 will provide the Monitor and Control functions via a PC and will also allow for software downloading.

The converter is fully synthesized with the PLL oscillators either locked to a highly stable internal 10 MHz reference or if the external reference option is fitted and the proper level of signal is present, the PLL will automatically lock to the external reference.

### Options

- Ethernet port and SNMP Interface
- Redundant Ready (for 1:N)
- Rack Mount set of slides

### Operating Bands

Up-Converters		
Model Number	Input	Output
ARUN-LC-WEK	Any 51 MHz band within 1150-1600 MHz	Any 51 MHz band within 6.6-7.075 GHz

Down-Converters		
Model Number	Input	Output
ARDN-CL-WEK	Any 51 MHz within 6.6-7.075 GHz	Any 51 MHz within 1150-1600 MHz

### Application

The WEK range of converters is particularly suited for use in WAAS and EGNOS Networks, that provide accurate location indication, by correcting the GPS signal provided. This makes them an ideal choice for large earth stations specialized in WAAS or EGNOS applications. The lightweight, rugged and compact design also ensures that the WE converter provides the ideal solution for mobile satellite systems. With fully welded aluminum chassis and robust modular internal construction the converter can even meet the demands of military installations. The WEK range of converters provides an industry leading MTBF of over 250,000 hours.

### Redundancy

For systems requiring redundancy Advantech Wireless can provide 1:1, 1:2 and 1:N (up to 12) solutions. The 1:N redundancy is provided by the 1:N Controller and the Switch Panel. Each Switch Panel can handle up to four (4) converter units. A 1:12 system requires one Controller panel plus three Switch Panels. A complete 1:12 complete system occupies a space of 17U.

## C-Band Synthesized Frequency Converter WAAS/EGNOS Compliant

### Technical Specifications

Up-Converter		Down-Converter	
IF Input		RF Input	
Frequency range	Any 51 MHz band within 1150-1600 MHz	Frequency range	Any 51 MHz within 6.6-7.075 GHz
Tuned Frequency	10 Hz step	Tuned Frequency	10 Hz step
Impedance	50 $\Omega$	Impedance	50 $\Omega$
Input Connector	N-type (female)	Input Connector	SMA (female)
Return loss	18 dB	Return loss	18 dB
RF Output		IF Output	
Frequency range	Any 51 MHz within 6.6-7.075 GHz	Frequency range	Any 51 MHz within 1150-1600 MHz
Output Level	+27 dBm at P1dB	Output level	+10 dBm at P1dB
IMD3 (two tone)	-40 dBc max @ 17 dBm output	IMD3 (two tone)	-40 dBc max @ 0 dBm output
Output connector	SMA (female)	Output Connector	Type N ( female )
Connector Impedance	50 $\Omega$	Connector Impedance	50 $\Omega$
Return loss	20 dB	Return Loss	20 dB
Noise Figure	15 dB at maximum Gain	Noise Figure	15 dB at maximum Gain
Transfer Characteristics		Transfer Characteristics	
Conversion Gain	40 +/- 1dB	Conversion Gain	25 +/- 1dB
Gain adjustment	40 dB (0.5 dB step size)	Gain adjustment	25 dB (0.5 dB step size)
Gain flatness	1.0 dB p-p max. 51 MHz	Gain flatness	1.0 dB p-p max. 51 MHz
Gain stability	$\pm 0.25$ dB max. /24 hours $\pm 1$ dB over temp. range	Gain stability	$\pm 0.25$ dB max. / 24 hours $\pm 1$ dB over temp. range
Spurious	< -55 dBc @ -10 dBm output, any gain settings	Spurious	< -55 dBc @ -10 dBm output, any gain settings
Group delay stability (over 51 MHz)	+/- 0.5 ns p-p /day at constant temperature	Group delay stability (over 51 MHz)	+/- 0.5 ns p-p /day at constant temperature
Phase noise common for up and down converter		Monitor and Control	
@ offset	Single Side Band Phase Noise (max.)	RS 485	DB9
1 Hz	-37 dBc/Hz	RS 232	DB9
4 Hz	-48 dBc/Hz	Discrete	DB9
10 Hz	-55 dBc/Hz	Ethernet (optional)	RJ45 F (optional)
100 Hz	-75 dBc/Hz		
1 kHz	-90 dBc/Hz		
10 kHz	-95 dBc/Hz		
100 kHz	-100 dBc/Hz		
1 MHz	-110 dBc/Hz		
Reference		Mechanical	
External Reference	10 MHz, 0 +/- 2 dBm ( Optional)	Dimensions	Width 19" (482.6 mm)
Internal reference stability	$5 \times 10^{-11}$ / 1 to 10 seconds		Height 1U 1.75" (44.5 mm)
			Depth 22" (558.8 mm)
Environmental		Power Supply	
Operational	0°C to +50°C standard	Voltage	90 – 265 VAC (47 – 63 Hz)
Storage	-55°C to +85°C	Power	40W (typical, single converter)
Humidity	Non-condensing	Connector	IEC 603320 10A
Altitude	3,000m AMSL		

Ref.: PB-FCS2001-LC-WEK-001-20114

#### NORTH AMERICA

**USA**  
info.usa@advantechwireless.com

**CANADA**  
Info.canada@advantechwireless.com

#### EUROPE

**UNITED KINGDOM**  
info.uk@advantechwireless.com

**RUSSIA & CIS**  
info.russia@advantechwireless.com

#### SOUTH AMERICA

info.latam@advantechwireless.com

**BRAZIL**  
info.brazil@advantechwireless.com

#### ASIA

info.asia@advantechwireless.com

**INDIA**  
info.india@advantechwireless.com